

## 4EVAC Fireman Microphone Panel version 4E-FMP

Author

DD

Revision

V01

Date

14-10-2020



### Technical specifications

#### 4E-FMP

4E-FMP is a spare part compatible with 4EVAC voice alarm equipment.

Transducer type	MEMS
Directional pattern	Hyper-cardioid
Frequency response	20Hz – 20kHz
Connector	5-pin connector, proprietary 4EVAC
Manual controls	Built-in PTT switch
Surveillance	PTT switch, mic capsule monitoring
Housing	ABS/ rubber
Dimensions (H x W x D)	14x8x4,5cm
Packaging (H x W x D)	22x22x16cm
Cable length	30cm – 1m
Weight (incl. cable)	205gr

All information provided in this document is subject to change without notice. 4EVAC may also make improvements and/or changes in the products described in this information at any time without notice.

### General information

4E-FMP is the first microphone with PTT switch, compatible with 4EVAC voice alarm equipment. It is designed as emergency fireman's microphone supporting full surveillance of the microphone transducer as well as PTT switch. It's 5-pin connector is specific for 4EVAC equipment exclusively.


4E-FMP is built in the following 4EVAC equipment:

- Compact 500 (All-in-one voice evacuation system);
- 4E-FM (Fireman's microphone)
- 4E-FMT (Fireman's microphone with touchscreen)
- 4E-FMTC (Fireman's microphone with touchscreen and commercial purpose gooseneck mic)
- 4E-FMWB (Wall-box fireman's microphone)

4E-FMP can also be integrated with 4E-GPIO, creating hardware base for custom emergency panels with manual control and emergency microphone.



4EVAC equipment compatible with 4E-FMP

Hacousto Holland bv Industrieweg 87 2651BC Berkel & Rodenrijs				
<b>4EVAC Fireman Microphone Panel version 4E-FMP</b>	Author	DD	Revision	V01
			Date	14-10-2020



4EVAC is a trade name of:

Hacousto Holland bv  
Industrieweg 87  
2651BC Berkel & Rodenrijs  
The Netherlands

[www.4EVAC.com](http://www.4EVAC.com)